



SR5006 Home Theater Receiver

The SR5006 delivers the kind of convenience, network capability and power that's sure to exceed your home entertainment needs for years to come. A newly styled front panel, complete with "star and circle" display, recalls the classic components that have made Marantz an audiophile favorite for decades. AirPlay allows you to stream music wirelessly; from your iPhone, iPod Touch and iPad; over your home network, and you're sure to enjoy streaming audio content from online music services like Pandora, Rhapsody and Napster as well as from your own shared media files. Access thousands of Internet radio stations from all over the world or dial in the ultimate set up with Audyssey MultEQ-XT room correction, Dynamic EQ and Dynamic Volume. Two audio zones help deliver seamless audio content all around the house while a Set Up Wizard insures you'll be up and running in no time.

AUDIO/VIDEO CONNECTIONS

- 7.1 Channels
- AM/FM Tuner
- 56Tuner Presets: Group A-G: each 8 channels
- 6 RCA Analog inputs (incl. Front RCA)
- 2 Optical, 2 Coaxial SPDIF Digital Inputs
- 6/1 HDMI ver.1.4a In/Out
 - CEC (Control)
 - ARC (Audio Return Channel)
 - HDMI In Stand By
 - Auto Lip Sync.
 - Deep Color, x.v.Color
 - Pass through in Standby mode
- 2/1 Component In / Out
- 5/1 Composite In / Out
- Assignable HDMI / Component inputs
- Front USB input for digital iPod Connection
- 7.1 Channel Input
- Headphone Out
- Assignable 2.1 Channel Preamp-Out
- Speaker A or B Switching

ADVANCED CONNECTIONS

- iPhone/iPod Digital Connection
- Bluetooth Wireless Audio Transmission Capability
- External IR Receiver
- Marantz D-Bus(RC-5), Remote In / Out, RS232

AUDIO/VIDEO PROCESSING

- ANALOG DEVICES: SHARC 32-bit Processor
- Dolby: True HD/Digital Plus&EX/Pro Logic IIz, IIx
- Dolby: II/Virtual Speaker/Headphone
- DTS: HD Master&High Res. Audio/ES/96/24/
- DTS: Discrete&Matrix6.1/Neo:6/Express
- DTS Neural Surround
- Multi Ch Stereo
- Audyssey MultEQ-XT Auto Calibration w/ MIC
- Audyssey Dynamic EQ / Dynamic Volume
- 9 Band EQ, -20dB - +6dB
- Independent Crossover Setting for each speaker
- Lip-sync (digital audio delay) 0-200 msec
- Volume Control Setting: Limit, Power On Vol
- Mute Level, Display type (dB or 0-99)
- Component/Composite to HDMI Trans-coding
- OSD output over HDMI

USER CONFIGURABLE FEATURES

- Input Level Adjust
- Input Assign (Component In/Digital In)
- Input Rename
- Input Skip
- On Screen Display (TEXT)
- Display Status Info.
- Software Upgradable

NETWORK FEATURES

- Ethernet port
- WEB Interface
- IP-based control, system backup/restore
- DLNA1.5 certified
- Stream audio and photos from all connected PC's
- vTuner Internet Radio w/ 14000 pre-loaded stations
- Stream audio and photos from Internet:
 - Rhapsody
 - Pandora
 - Napster
 - Flicker
- App Control

MARANTZ AUDIO ADVANTAGE

- All-discrete, 100w x 7 Class AB Output Stage
- High Current Linear Power Supply
- EI Core Power Transformer
- Pure Direct / Source Direct
- M-DAX (Marantz Dynamic Audio eXpander)
- Front Bi-Amp Drive Capability (Speaker C)
- Two audio zones
- Fully Discrete Amplification
- 192kHz/24-bit Audio DACS



SR5006 Home Theater Receiver

Audio Section

• Power amplifier

Rated output: Front:

100 W + 100 W (8 Ω, 20 Hz – 20 kHz with 0.08 % T.H.D.)

Center:

100 W (8 Ω, 20 Hz – 20 kHz with 0.08 % T.H.D.)

Surround:

100 W + 100 W (8 Ω, 20 Hz – 20 kHz with 0.08 % T.H.D.)

Surround back:

100 W + 100 W (8 Ω, 20 Hz – 20 kHz with 0.08 % T.H.D.)

Output connectors: 6 – 8 Ω (SPEAKER A+B: 8 Ω)

• Analog

Input sensitivity/Input impedance: 200 mV/47 kΩ

Frequency response: 10 Hz – 100 kHz — +1, –3 dB

(DIRECT mode)

S/N: 100 dB (IHF–A weighted, DIRECT mode)

Video Section

• Standard video connectors

Input/output level and impedance: 1 Vp-p, 75 Ω

Frequency response: 5 Hz – 10 MHz — 0, –3 dB

• Color component video connector

Input/output level and impedance: Y (brightness) signal

– 1 Vp-p, 75 Ω

PB / CB signal — 0.7 Vp-p, 75 Ω

PR / CR signal — 0.7 Vp-p, 75 Ω

Frequency response: 5 Hz – 60 MHz — 0, –3 dB

Tuner Section [FM] [AM]

(Note: μV at 75 Ω, 0 dBf = 1 x 10–15 W)

Receiving Range: 87.5 MHz – 107.9 MHz 520 kHz – 1710

kHz

Usable Sensitivity: 1.2 μV (12.8 dBf) 18 μV

50 dB Quieting Sensitivity: MONO 2.8 μV (20.2 dBf)

S/N: MONO 70 dB (IHF–A weighted, DIRECT mode)

STEREO 67 dB (IHF–A weighted, DIRECT mode)

Total harmonic Distortion (at 1 kHz): MONO 0.7 %

STEREO 1.0 %

General


Power supply: AC 120 V, 60 Hz

Power consumption: 650 W

0.2 W (Standby)

3 W (CEC standby)

For purposes of improvement, specifications and design are subject to change without notice.



because music matters

All specifications, dimensions and weights are subject to change without notice.
D&M Holdings, Marantz, Marantz America, LLC or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors
Being made by dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.

©2011 Marantz America, LLC · www.marantz.com