



The DN-AVRX3300 7.2ch surround AV receiver features Dolby Atmos decoding for the ultimate immersive audio experience. The 4k/60Hz full-rate pass-through, built-in dual-band Wi-Fi and Bluetooth, and 105W per channel speaker outputs make this powerhouse the perfect audio and video receiver. Connect to your internal network via the RJ-45 Ethernet LAN port and enjoy streaming services such as Spotify, Pandora and SiriusXM - and also choose from thousands of global Internet radio stations. AirPlay enables wireless connectivity from iPod Touch®, iPhone® and iPad®.

## FEATURES

- 7.2 channel AV Receiver with 105W per channel (8ohms, 20Hz – 20kHz with 0.08% T.H.D.)
- Built-in Wi-Fi with 2.4GHz/5GHz dual band support; built-in Bluetooth
- 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020
- 8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 2 HDMI outputs
- Dolby Atmos® (up to 5.1.2) and DTS:X™ (via firmware update)
- Advanced Multi-Room options; 7.2ch Pre-out; RS232 Control
- AirPlay®, Bluetooth®, Internet Radio, Spotify Connect®, Pandora®, SiriusXM™ Network Audio Streaming



## DN-AVRX3300 | 7.2ch AV Surround Receiver with Wi-Fi, Bluetooth and Ethernet Connectivity

### NUMBER OF POWER AMPS

7 (Front L/R, Center, Surround L/R, Surround Back L/R)

### POWER OUTPUT

215 watts per channel (maximum power output per channel)

135 watts per channel (6 ohms, 1 kHz, THD 0.7%, 2ch driven)

105 watts per channel (8 ohms, 20 Hz - 20 kHz, THD 0.08%, 2ch driven)

**Speaker Impedance:** 4-16 ohms

### PREAMPLIFIER SECTION

**Input Sensitivity:** Impedance 200 mV / 47 kohms

**Frequency response:** 10 Hz - 100 kHz — +1, -3 dB (DIRECT mode)

**S/N Ratio:** 100 dB (IHF-A weighted, DIRECT mode)

### FM SECTION

Tuning frequency range: 87.5 - 107.9 MHz

### AM SECTION

Tuning frequency range: 520 kHz – 1710 kHz

### IN

HDMI (Front 1) x 6

Component (video) x 2

Analogue Audio x 5

Digital Optical / Coaxial x 2 / x 2

USB (front) x 1

### OUT

HDMI Monitor / Zone 2 x 1 / x 1

Composite Monitor x 1

Audio Preout (SW) 7.2 ch

Zone 2 Preout 2.0 ch

Phones x 1

### OTHER

Ethernet x 1

Setup Microphone Port x 1

FM Tuner Antenna x 1

AM Tuner Antenna x 1

RS232 / 12 V Trigger out x 1 / x 1

### GENERAL

**Power Supply:** AC 120 V / 60 Hz

**Power Consumption:** 600 W (Standby 0.1 W, CEC standby 0.5 W)

**Power Consumption:** No-Sound 45 W (ECO on), 80 W (ECO off)

**Dimensions:** (W x H x D) 17.1 x 15.3 x 6.6 inches (434 x 389 x 168mm)  
(without rack ears)

**Weight:** 23.8 lbs (10.8kg) (without rack ears)

### IN THE BOX

- DN-AVRX3300
- Power Cable
- Remote Control
- Rack Ears & Screws
- FM Indoor Antenna
- AM Loop Antenna
- Sound Calibration Microphone
- Sound Calibration Microphone Stand
- User Guide
- Safety & Warranty Manual

### WARRANTY

1-Year Limited